



15-2



15-1 15-3 15-2-3



DTMO-1 DTMA-1



DTMO-2 DTMA-2
DTMOMA-2



491



492



3625-0324-107



Desk Top Controls

Under Desk Top Mounting

The SDC 15 series switch controls are mounted on the underside of a desk for remote door control. They may be connected to the REX input of an access control or to the trigger input of a time delay relay to allow timed access and egress. The 15-2-3 is equipped with one momentary switch to provide momentary access and a toggle switch for sustained bypass.

- 15-1 On-off push switch, 6 Amp
- 15-2 Momentary push switch, 10 Amp
- 15-3 On-off toggle switch, 6 Amp
- 15-2-3 On-off toggle switch and momentary push switch, 6 Amp

Contact: SPDT, 6 Amps @ 30VDC

Dimensions: 15-2
1"H x 2.25"W x 2.5"D (25.4 x 57.2 x 63.5mm)
15-1 / 15-3 / 15-2-3
1.125"H x 3.125"W x 1.5"D (28.6 x 79.4 x 38.1mm)

Mini Desk Top Console

The SDC DT series consoles have a clean look for desktop applications. The heavy duty momentary push switches may be connected to the REX input of an access control or trigger input of a time delay relay. The maintained switch station may be wired to provide sustained bypass (unlock). When connected to a door status switch (DPS) or magnetic bond sensor (BAS), the bi-color LED can provide status indication of the door and/or locking device.

- DTMO-1 One Momentary station and one LED
- DTMO-2 Two Momentary stations and two LEDs
- DTMA-2 Two Maintained stations and two LEDs
- DTMOMA-2 One Momentary station and 1 maintained station and two LEDs

Contact: SPDT, 5 Amps @ 30VDC

Dimensions: 4.125"W x 3.125"H x 6.25"D (79.4 x 104.8 x 158.8mm)

LED: One, tri-color LED. Illuminates red, or green or amber

Finish: Gloss Beige

Material: 0.0936" (2.286mm) aluminum

Power: 24VDC @ 0.02 Amp required for each LED

Emergency Door Release

The SDC 490 Series Emergency Door Release is ideal for immediate unlocking of doors that are equipped with failsafe electric locks and may influence approval of an electric lock system. The built in alarm may be used as a local door annunciator.

491 Features:

- Alarm
- 2-SPDT 10 Amp contacts
- Remote monitoring
- CCTV activation, or alarm activation
- Single gang box mounted
- Two replacement glass plates included

491 Break glass emergency door release
3V-28VDC, 18mA with siren (blue)

491-GL4 Four replacement glass plates

491-BB Surface mount back box (blue)

492 Features:

- Alarm
- 2-SPDT 10 Amp contacts
- Blue housing with easy read activation instructions
- Release of one or all doors on same circuit
- Single gang box mounted

492 Pull station emergency door release
3V-28VDC, 18mA with siren (blue)

492-GL4 Four replacement glass rods

492-BB Surface mount back box (blue)

