



DITEK Corporation
ONE DITEK CENTER
1720 Starkey Road
Largo, FL 33771

INSTALL INSTRUCTIONS

DTK-TSS4/DTK-TSS4D

This Surge Protective Device (SPD) is a high performance device, designed to provide protection for sensitive electronic loads connected to service panels, fire panels, or where the SPD is directly connected to the electronic device. Maximum protection will only be achieved if the SPD is properly installed. Please read and follow the installation instructions carefully.

NOTICE: This SPD should be installed by a qualified electrician in accordance with the National and Local Electrical Codes and the following instructions.

APPLICATION

Surge suppression for hardwired series installations on 120 VAC single branch circuits. Model DTK-TSS4D has Dry Contacts for remote notification of surge protection status.

INSTRUCTIONS:

Caution: Measure all voltages to insure applied voltage does not exceed the voltage rating of the unit. Improper installation voids the warranty.

NOTE: This device is suitable for use on a circuit capable of delivering not more than 10,000 RMS symmetrical amperes when protected by a circuit breaker rated: 25A and minimum 120 Volts. This SPD contains no serviceable parts.

NEMA ENCLOSURE MOUNTING

Enclosure can be mounted directly on to a panel, frame, or other mounting surface through corner mounting holes that are visible when the cover is removed. Punch 1 knockout on each end of the enclosure to allow for the input and output wiring connections. **Corner hole mounting and liquid tight connectors are required to maintain the NEMA 4X rating.**

DTK-TSS4/DTK-TSS4D WIRING INSTRUCTIONS

1. Turn off the power at the circuit breaker or main before beginning installation.
 2. Securely mount this unit in series between the supply wiring and the equipment to be protected.
 3. Allow 3 feet of conductor length between this device and the protected equipment. This will allow the unit time to react.
 4. Use minimum 12 AWG stranded wire for all hook ups.
 5. Remove the top nut from the input, output and ground lugs. (Do not remove the lower lock nut)
 6. Connect the ground (Green or Bare) supply and protected equipment wires to the ground lug using one of the supplied ring terminals, replace the nut and torque to 10 inch pounds.
- Ground Resistance Rule:** Max ground resistance is 25 Ohms, 5 Ohms or less is optimum. This cannot be an assumed value and must be measured to assure proper grounding.
7. Connect the neutral (White) supply and protected equipment wires to their respective neutral lugs using 2 of the supplied ring terminals, replace the top nuts and torque to 10 inch pounds.
 8. Connect the line (Black) supply and protected equipment wires to their respective line lugs using 2 of the supplied ring terminals, replace the top nuts and torque to 10 inch pounds.
 9. Install the plastic cover placing it over the threads and fasten with the included nylon nuts until snug.
 10. After all connections have been made and no hazards exist, restore power.
 11. Verify that the LED is on signifying surge protection active, AC power present and ground OK.

DTK-TSS4D DRY CONTACT OPERATION

The Dry Contacts are a SPDT Form 1C circuit rated 120V/0.5A, designed for low voltage or control signals only, and activate if the Phase leg loses its surge protection. The Dry Contacts are accessed by a three position terminal block (#16-28 AWG). The positions are marked Common (C), Normally Open (NO), and Normally Closed (NC). If the surge protection is lost, the contacts will reverse; Normally Open will Close and Normally Closed will open. There is no change to the Common (C).







DITEK Corporation
ONE DITEK CENTER
1720 Starkey Road
Largo, FL 33771

INSTALL INSTRUCTIONS

DTK-TSS4/DTK-TSS4D

Illustrations Page



EXPECTED SYSTEM VOLTAGES			
120 VAC	L-N	L-G	N-G
VOLTAGES	120	120	0

