POWER SUPPLIES

US MADE TRANSFORMERS BY FUNCTIONAL DEVICES

US TRANSFORMERS



These US Made Transformers come in 40VA, 50VA and 100VA options. They are Class 2 and have UL, CE and cUL approvals. They all feature split bobbin construction. Some also have a secondary circuit breaker.

FEATURES

- · Foot and Hub mounted models available
- Class 2 rated
- Color coded wire leads
- Meets Buy American ARRA 2009



WIRING

208 VAC

Primary Wires 480 VAC Gray **277 VAC** Brown **240 VAC**


Orange Red

120 VAC White Common Black **Secondary Wires 24 VAC** Yellow **24 VAC** Yellow/White


SPECIFICATIONS

Model	Supply Voltage	Supply Frequency	Secondary Voltage	Over Current Protection	Mounting	Weight
TR40VA001US	120VAC	50/60Hz	24VAC	Inherently Limited	Foot & Single Threaded Hub	2.02 lbs.
TR40VA002US	120VAC	50/60Hz	24VAC	Inherently Limited	Foot & Dual Threaded Hubs	2.05 lbs.
TR50VA001US	120VAC	50/60Hz	24VAC	3 Amp Fuse	Foot & Single Threaded Hub	2.14 lbs.
TR50VA022US	120/208/240/277/480VAC	50/60Hz	24VAC	Circuit Breaker	Foot & Dual Threaded Hubs	3.04 lbs.
TR50VA005US	120VAC	50/60Hz	24VAC	Circuit Breaker	Foot & Single Threaded Hub	2.60 lbs.
TR100VA001US	120VAC	50/60Hz	24VAC	Circuit Breaker	Foot & Single Threaded Hub	4.06 lbs.
TR100VA002US	120VAC	50/60Hz	24VAC	Circuit Breaker	Foot & Dual Threaded Hubs	4.13 lbs.
TR100VA004US	120/240/277/480VAC	50/60Hz	24VAC	Circuit Breaker	Foot & Dual Threaded Hubs	4.60 lbs.

DIMENSIONS



	DIMENSIONS in (cm)					
MODEL	A	В	С	D	E	STYLE
TR40VA001US	2.7 (6.9)	2.2 (5.6)	2.875 (7.3)	1.75 (4.4)	1.93 (4.9)	1
TR40VA002US	2.7 (6.9)	2.2 (5.6)	2.875 (7.3)	1.75 (4.4)	1.93 (4.9)	2
TR50VA001US	2.75 (7)	2.2 (5.6)	2.875 (7.3)	1.75 (4.4)	1.93 (4.9)	1
TR50VA022US	3.5 (8.9)	2.525 (6.4)	3.25 (8.3)	2 (5.1)	1.95 (5)	4
TR50VA005US	3.5 (8.9)	2.525 (6.4)	3.25 (8.3)	2 (5.1)	1.95 (5)	5
TR100VA001US	3.5 (8.9)	2.5 (6.4)	3.25 (8.3)	2 (5.1)	2.55 (6.5)	1
TR100VA002US	3.5 (8.9)	2.5 (6.4)	3.25 (8.3)	2 (5.1)	2.55 (6.5)	2
TR100VA004US	3.5 (8.9)	2.5 (6.4)	3.25 (8.3)	2 (5.1)	2.75 (7)	4



ORDERING INFORMATION

MODEL	DESCRIPTION
TR40VA001US	US made 40VA, 120-24V inherent limit, 1 HUB
TR40VA002US	US made 40VA, 120-24V inherent limit, 2 HUB
TR50VA001US	US made 50VA, 120-24V, 1 HUB, 3A fuse
TR50VA022US	US made 50VA, 480/277/240/208/120, 24V, 2 HUB, circuit breaker
TR50VA005US	US made 50VA, 120-24V, 1 HUB, circuit breaker
TR100VA001US	US made 96VA, 120-24V, 1 HUB, circuit breaker
TR100VA002US	US made 96VA, 120-24V, 2 HUB, circuit breaker
TR100VA004US	US made 96VA, 480/277/240/120, 24V, 2 HUB, circuit breaker

March 2014